



□□□□□□□□ □□□□ □□□□□□□□□□ □□□□□□□□□□□□
□□□□□□□□□□

Y-500U

(m m)

[illegible]

`00000072kg-1055°C4131F)5,`

□ □ □ □ □

- [illegible]

8. 請說明

A: 請說明

B: 請說明

C: 請說明

請說明OEM/ODM



1

Aluminum alloy

Power off the open circuit design,
once locked In addition to power
or the lock tongue can not

2



3

To prevent illegal insert fragment
magnet lock, after the lock is not
affected by External disturbance




Hex socket screw

4



5



Time delay with 0/3/6Second






STANDARD INSTALLATION STEPS


Professional guidance, Rest assured



1 Fold the plate to 90° .




2 Close the door first, then place the upper side of template on door frame, while adjust the left side next to the door leaf.




3 Mark screw positions of armature plate and magnetic lock on door leaf and door frame respectively.




4 Drill holes based on the marked positions.




5 Make a combination based on the picture.



6 Strike the pin into the armature plate slightly (to avoid movement).




7 Make a combination based on the picture (add washer accordingly). The rubber ring must be added.



8 Place the rubber ring between armature plate and door leaf.




9 Use Allen key to remove the mounting plate from lock body.




10 Fix the mounting plate on the door frame according to the holes drilled earlier.




11 Use Allen key to screw the lock body on the mounting plate.




12 Close the door to test holding force. The angle between armature plate and magnetic lock can be adjusted by adding or reducing washers.




13 After all the appropriate procedures, the holding force can be maximized. Finally, fix the tamper screw.



Hollow Metal Door
Drill a hole
Inside: Diameter is 8mm
Outside: Diameter is 16mm



Wooden Door
Drill a hole
Inside: Diameter is 8mm
Outside: Diameter is 12.7mm



Metal Surface Door
Inside: Drill a hole
diameter is 8mm folding
the plastic straight pin

Notice:

Thickness of Door Leaf:

350LBS: 44mm

600LBS: 50mm

800LBS: 48mm

1200LBS: 46mm



11

ACM-Y500A



5608-800-2

ELECTRIC DROP BOLT LOCK

1pcs Made in China



3

20
"



ACM-Y100S 2PIN

100MA / 900MA
 2PIN

ACM-Y500A

NC

ACM-Y100S 5PIN

□□□□□□□□□□

[illegible]

You May Need

**ACM-Y280**

□□□□□□□□ (280kg/600□□□)

ACM-Y100S

□□□□□□□□□□ (NC/NO) □□□□□□□□

□□PVC □□□

ACM-Y066

□□□□□□□□□□□□□□□□□□□□
□□□□□□: 130x98x41mm□□□□

□□□□□□□□□□□□□□□□□□□□



ACM-Y700

□□□□□□□□□□□□□□□□□□□□

ACM-Y600

□□□□□□□□□□□□□□□□□□□□

ACM-Y601

□□□□□□□□□□□□□□□□□□□□

□□□□□□□□□□ □□□□□□□□



ACM-WEG02

□□□□□□ 2 □□ □□ □□□□□□ □□□
(RS232□RS485 □□□ TCP/IP □□)

ACM-K2A

□□□□□□□□□□□□□□□□□□□□K2A:
115*40mm;K2B: 86*86mm

ACM-Y806-3A

□□□□□□□□ 12V/3A

- 1) 24 小時服務熱線
- 2) 專業技術支持
- 3) OEM/ODM 服務
- 4) 產品質量保證
- 5) 服務範圍：
- 1) 全國各省市
- 2) 全國各省市
- 3) 全國各省市 2、3 級代理商
- 6) 服務時間： 上午 9 時至下午 5 時 7) 30 分鐘
- 7) 服務： 全國各省市 服務熱線： T/T 服務熱線
- 8) 服務： DHL、FEDEX、TNT、UPS、EMS、SEA、AIR 服務熱線
- 服務
- 服務
- 全國各省市 2 級代理商
- 全國各省市 2 級代理商
- 全國各省市 2 級代理商

11

ACM□□□□□□□□□□□□□□□□

RFID 1 20 RFID
RFID RFID RFID RFID
RFID UHF

